

DCP-L3560CDW
Colour LED Multi-Function Centre

brother
at your side



PRINT



SCAN



COPY

Colourful and Connected LED Multi-Function Printer

High productivity Colour Multi-Function Centre with 2-Sided printing, Dual Band Wireless, Gigabit Ethernet Connectivity, and 3.5" Touch Screen Panel



Up to 26ppm
(mono/colour)



Auto 2-sided
Printing



Security
Function



Wireless
Connectivity



Mobile Printing
& Scanning

www.brother.in

DCP-L3560CDW

Key Functions	Print, Scan, Copy
Description	High productivity Colour Multi-Function Centre with 2-Sided printing, Dual Band Wireless, Gigabit Ethernet connectivity, and 3.5" touch screen panel
Print Speed (A4/Letter)	Up to 26/27 ppm
Print Resolution	Upto 600 x 2,400 dpi
First Print Out Time (Ready)	Less than 13.5/13.5 secs (Mono/Colour)
2-Sided Feature (Auto Duplex Printing)	Automatic 2-Sided Printing
CONNECTIVITY/NETWORKING	
Interface	USB 2.0, Gigabit Ethernet (10Base-T/100Base-TX/1000Base-T), Wi-Fi Direct, Dual Band Wireless LAN (2.4GHz/5.0GHz)
Mobile Solutions	AirPrint, Mopria and Brother iPrint&Scan
Desktop Solutions	Brother iPrint&Scan
Brother's Cloud Apps	Yes
WebConnect	Yes
COPY FUNCTIONS	
Copy Speed (A4/Letter)	Up to 26/27 cpm
Copy Resolution	600 x 600 dpi
Reduction / Enlargement Ratio	25% - 400% in 1% increments
Copy Features	N in 1
SCAN FUNCTIONS	
Scan Speed (Mono/Colour) ¹	27/21 ipm (A4) 29/22 ipm (LTR)
Scan Technology	CIS
Resolution (Optical)	Max 1,200 x 1,200 dpi
Resolution (Interpolated)	Max. 19,200 x 19,200 dpi
Scan-to Functions	Sharepoint, E-mail, Image, OCR, File, FTP, FTPS, Network (Windows Only)
PAPER HANDLING	
Input Tray (Standard)	250 Sheets
Multi-purpose Tray/Manual Slot	1 Sheet
Output Tray (Face Down)	150 Sheets Face Down (80g/m ²) 1 Sheet Face Up (straight paper path)
Automatic Document Feeder (ADF)	50 Sheets
Media Weights (Standard Tray/MP Tray)	60 to 163g/m ² (Using Manual Feed Slot)
Media Size (Standard Tray)	A4, Letter, Legal, Mexican Legal, India Legal, Executive, A5, A5 Long Edge, A6, JIS B5, A4 Short(270mm), Folio, 16K (195 x 270 mm)
OTHERS	
Processor Speed	Main: Cortex-A53 800MHz Sub: ARM946 133MHz
Memory	512MB
Display	3.5" TFT Colour LCD
OS Compatibility	Windows : Win10, 11 / Server 2012 / 2012R2 / 2016 / 2019 / 2022 Linux : CUPS, LPD/LPRng (x86/x64 environment)
Utilities & Solutions	BRAdmin Light*, BRAdmin Professional 4*, Web Based Management
Security Features	Setting Lock, Secure Function Lock, Secure Print, Active Directory, LDAP
Power Consumption (Printing/Sleep)	Printing: Average: Approx. 560W Sleep mode : Average: Approx. 10W
Power Source Noise Level (Printing)	220-240V AC 50/60Hz
Noise Level (Printing)	LpAm = 47 dB(A)
SUPPLIES	
Inbox Toner Yield	BK: Approx. 1,000 pages CMY: Approx. 1,000 pages
Standard-Yield Toner (TN269) ⁱⁱ	BK: Approx. 1,500 pages CMY: Approx. 1,200 pages
High-Yield Toner (TN269XL) ⁱⁱ	BK: Approx. 3,000 pages CMY: Approx. 2,300 pages
Drum (DR269CL)	Approx. 20,000 pages
DIMENSIONS & WEIGHT	
Dimension (W X D X H)	410 x 444 x 401 mm
Weight w/o Carton, w/ toner/drum	20.1 kg

*For Windows by download only ¹ In accordance with ISO/IEC17991ⁱⁱ ⁱⁱ In accordance with ISO/IEC 19798

India EPR Compliance | Entity Name: Brother International (India) Private Limited

Plastic Waste EPR No.: BO-13-000-08-AADCBO263E-22 | Battery Waste EPR No.: 6821475 | Thickness for PE bag: 50 microns or above



Working with you for a sustainable future.
www.brotherearth.com



One-stop centre for free downloadable templates



Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yields per consumable, protection of your machine from damages and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damages arising from the use of non-genuine consumables.

Brother International (India) Private Limited

☎ • 1-800-222-422 • 1-800-209-8904 (Toll Free)

✉ • customercare@brother.in | 🌐 • www.brother.in

Operating Hours:

📅 Monday - Friday | Saturday
🕒 8:30 AM - 6:30 PM | 9:00 AM - 6:00 PM
🚫 Closed on Sunday & Public Holidays



SCAN TO CHAT

7045 450 450



SCS

