

## **CURRENCY COUNTERS**

## **GB 502 MV**



Sensors Hopper Capacity Stacker Capacity Counting Speed Dimension Power Consumption Counting Display LCD Colour Display LCD Colour Display UV, MG, IR, MT 200 1000pcs/min 290 x 255 x 165 mm ≤80W 4 digits LCD Turns red with Fake Note	SPECIFICATION	
Stacker Capacity Counting Speed Dimension Power Consumption Counting Display LCD Colour Display  Stacker Capacity 200 1000pcs/min 290 x 255 x 165 mm ≤80W 4 digits LCD Turns red with Fake Note	Sensors	UV, MG, IR, MT
Counting Speed Dimension Power Consumption Counting Display LCD Colour Display  LCD Colour Display  1000pcs/min 290 x 255 x 165 mm ≤80W 4 digits LCD Turns red with Fake Note	Hopper Capacity	200
Dimension  Power Consumption Counting Display LCD Colour Display  LCD Colour Display  Note  290 x 255 x 165 mm  ≤80W  4 digits LCD  Turns red with Fake  Note	Stacker Capacity	200
Power Consumption Counting Display LCD Colour Display  LCD Colour Display  Turns red with Fake Note	Counting Speed	1000pcs/min
Counting Display LCD Colour Display Turns red with Fake Note	Dimension	290 x 255 x 165 mm
LCD Colour Display Turns red with Fake Note	Power Consumption	≤80W
Note	Counting Display	4 digits LCD
	LCD Colour Display	Turns red with Fake
		Note
Net Weight 6.3 kg	Net Weight	6.3 kg

- Automatic start, stop and clear.
- Automatic detecting with UV, MG, MT and IR while counting.
- Automatic half-note, chain note and double-note detection.
- With batch, add and self checking function.
- LCD color changes to red on detection of fake note.
- Manual value calculation function.
- Software can be updated through RS-232 port.
- Specially designed for Indian currency notes.

